

## DC Block on Inner Conductor 2.4mm Male to 2.4mm Female Operating From 100 MHz to 50 GHz



#### DC Blocks Technical Data Sheet

**PE8237** 

#### **Features**

- Inner DC Block
- Operates from 100 MHz to 50 GHz

Good Insertion Loss of 1.5 dB Max

### **Applications**

- Test & Measurement
- Ground Loop Elimination
- Signal to Noise Ratio (SNR) Improvement

### Description

Pasternack's PE8237 is an inner DC block with 2.4mm connectors. It has a blocking capacitor on the inner conductor and operates from 100 MHz to 50 GHz. Our 2.4mm DC block offers good insertion loss of 1.5 dB and has a maximum operating voltage of 75 Vdc. DC blocks are commonly used to filter out unwanted DC signals, while allowing AC drive signals to pass through. They can help improve signal to noise ratio (SNR), eliminate ground loops, or provide isolation in your test setup. All of Pasternack's DC blocks are in stock and available to ship same-day.

#### **Electrical Specifications**

Description	Minimum	Typical	Maximum	Units
Frequency Range	0.1		50	GHz
Impedance		50		Ohms
VSWR			1.75:1	
Insertion Loss			1.5	dB
Operating Voltage (DC)			75	Volts

### **Mechanical Specifications**

Size

Length1.125 in [28.58 mm]Width0.3 in [7.62 mm]Weight0.017 lbs [7.71 g]Housing Material and PlatingStainless Steel, Gold

Configuration

Design Inner DC Block
Package Type Connectorized

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: DC Block on Inner Conductor 2.4mm Male to 2.4mm Female Operating From 100 MHz to 50 GHz PE8237

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451



# DC Block on Inner Conductor 2.4mm Male to 2.4mm Female Operating From 100 MHz to 50 GHz



#### **DC Blocks Technical Data Sheet**

**PE8237** 

Description	Connector 1	Connector 2	
Туре	2.4mm Male	2.4mm Female	
Inner Conductor Material and Plating	Beryllium Copper, Gold	Beryllium Copper, Gold	
Coupling Nut Material and Plating	Stainless Steel, Gold		
Hex Size	5/16 inch		
Body Material and Plating	Stainless Steel, Gold	Stainless Steel, Gold	

### **Environmental Specifications**

**Temperature** 

Operating Range

+5 to +75 deg C

Compliance Certifications (see product page for current document)

#### **Plotted and Other Data**

Notes:

DC Block on Inner Conductor 2.4mm Male to 2.4mm Female Operating From 100 MHz to 50 GHz from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99.4% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: DC Block on Inner Conductor 2.4mm Male to 2.4mm Female Operating From 100 MHz to 50 GHz PE8237

URL: https://www.pasternack.com/50-ohm-2.4mm-inner-dc-block-0.1-50-ghz-pe8237-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Pasternack does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Pasternack does not assume any liability arising out of the use of any part or documentation.

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623

Phone: (866) 727-8376 or (949) 261-1920 • Fax: (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com

**PE8237 CAD Drawing**DC Block on Inner Conductor 2.4mm Male to 2.4mm Female Operating From 100 MHz to 50 GHz

