



MMCX Plug Right Angle to BNC Male Cable  
Using RG178 Coax , LF Solder

**RF Cable Assemblies Technical Data Sheet**

**PE38083LF**

**Configuration**

- Connector 1: MMCX Plug Right Angle
- Connector 2: BNC Male
- Cable Type: RG178

**Features**

- Max Frequency 1 GHz
- 70% Phase Velocity
- FEP Jacket

**Applications**

- General Purpose
- Laboratory Use

**Description**

Pasternack's PE38083LF MMCX plug right angle to BNC male cable using RG178 coax is part of our full line of RF components available for same-day shipping. Pasternack's flexible RF cable assemblies are ideal for applications where tight bends and flexure are required. This Pasternack MMCX to BNC cable assembly has a plug to male gender configuration with 50 ohm flexible RG178 coax. The PE38083LF MMCX plug to BNC male cable assembly operates to 1 GHz. The right angle MMCX interface on the RG178 cable allows for easier connections in tight spaces.

Custom versions of most RF cable assemblies can be built and shipped same day. Custom cable assembly lengths can be obtained by specifying the desired length on the web site at time of order or by contacting a sales representative. Other available RF cable assembly value added services include connector orientation or clocking, heat shrink booting and custom labeling. RF testing can also be performed to document the electrical performance of your cable assembly.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: [MMCX Plug Right Angle to BNC Male Cable Using RG178 Coax , LF Solder PE38083LF](#)



MMCX Plug Right Angle to BNC Male Cable  
Using RG178 Coax , LF Solder

## RF Cable Assemblies Technical Data Sheet

**PE38083LF**

### Electrical Specifications

Description	Minimum	Typical	Maximum	Units
Frequency Range	DC		1,000	MHz
VSWR			1.4:1	
Velocity of Propagation		70		%
Capacitance		29.4 [96.46]		pF/ft [pF/m]
Operating Voltage (AC)			170	Vrms

### Specifications by Frequency

Description	F1	F2	F3	F4	F5	Units
Frequency	50	100	250	500	1,000	MHz
Insertion Loss (Typ.)	0.114	0.138	0.208	0.305	0.444	dB/ft
	0.37	0.45	0.68	1	1.46	dB/m

### Mechanical Specifications

#### Cable Assembly

##### Cable

Cable Type	RG178
Impedance	50 Ohms
Inner Conductor Type	Stranded
Inner Conductor Material and Plating	Copper Clad Steel, Silver
Dielectric Type	PTFE
Number of Shields	1
Shield Layer 1	Silver Plated Copper Braid
Jacket Material	FEP, Tan
Jacket Diameter	0.072 in [1.83 mm]
Repeated Minimum Bend Radius	0.4 in [10.16 mm]

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: [MMCX Plug Right Angle to BNC Male Cable Using RG178 Coax , LF Solder PE38083LF](#)



MMCX Plug Right Angle to BNC Male Cable  
Using RG178 Coax , LF Solder

## RF Cable Assemblies Technical Data Sheet

**PE38083LF**

### Connectors

Description	Connector 1	Connector 2
Type	MMCX Plug Right Angle	BNC Male
Specification	BS EN 122340	MIL-STD-348A
Impedance	50 Ohms	50 Ohms
Contact Material and Plating	Brass, Gold	Brass, Gold
Contact Plating Specification	30 µin minimum	30 µin minimum
Dielectric Type	PTFE	PTFE
Body Material and Plating	Brass, Gold	Brass, Nickel
Body Plating Specification	3 µin minimum	100 µin minimum
Coupling Nut Material and Plating		Brass, Nickel
Coupling Nut Plating Specification		100 µin minimum

### Environmental Specifications

#### Temperature

Operating Range -55 to +155 deg C

**Compliance Certifications** (see [product page](#) for current document)

### Plotted and Other Data

Notes:

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: [MMCX Plug Right Angle to BNC Male Cable Using RG178 Coax , LF Solder PE38083LF](#)



## MMCX Plug Right Angle to BNC Male Cable Using RG178 Coax , LF Solder

### RF Cable Assemblies Technical Data Sheet

**PE38083LF**

#### How to Order

Part Number Configuration:

**PE38083LF**

- **xx**

**uu**

Unit of Measure:  
cm = Centimeters  
<blank> = Inches  
Length  
Base Number

Example: PE38083LF-12 = 12 inches long cable  
PE38083LF-100cm = 100 cm long cable

MMCX Plug Right Angle to BNC Male Cable Using RG178 Coax , LF Solder from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99.4% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: [MMCX Plug Right Angle to BNC Male Cable Using RG178 Coax , LF Solder PE38083LF](#)

URL: <https://www.pasternack.com/mmcx-plug-bnc-male-rg178bu-cable-assembly-pe38083lf-p.aspx>

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Pasternack does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Pasternack does not assume any liability arising out of the use of any part or documentation.