

BNC Female Bulkhead Mount Connector Solder Attachment Solder Cup Terminal, .350 inch D Hole



RF Connectors Technical Data Sheet

PE4015

Configuration

- BNC Female Connector
- MIL-STD-348A
- 50 Ohms
- Straight Body Geometry

Features

- Max. Operating Frequency 4 GHz
- Good VSWR of 1.5:1

Solder Cup Interface Type

Solder Attachment

Bulkhead

 Gold Plated Brass Contact • 30 µin minimum contact plating

Applications

- General Purpose Test
- Rack and Panel Mount Applications

Description

Pasternack's PE4015 BNC female bulkhead connector with solder cup terminal (.350 inch D hole) is part of our full line of RF components available for same-day shipping. Our BNC female connector operates up to a maximum frequency of 4 GHz and offers good VSWR of 1.5:1. This BNC bulkhead connector allows designers to create external connections on their product enclosures, and can be used in a variety of other rack mount and panel mount applications.

Our BNC female bulkhead connector PE4015 datasheet specifications and drawing with dimensions are shown below in this PDF. Pasternack's broad catalog of RF, microwave and millimeter wave connectors allows designers to configure and customize their signal connections however they like. Whether the need is to provide an I/O for a board design, or simply create a custom cable assembly configuration. Pasternack has the right connector for the job. Pasternack can also expertly build your custom cable assemblies for you and ship same-day.

Electrical Specifications

Description	Minimum	Typical	Maximum	Units
Frequency Range	DC		4	GHz
VSWR			1.5:1	
Operating Voltage (AC)			500	Vrms
Dielectric Withstanding Voltage (AC)			1,500	Vrms

Mechanical Specifications

Size

Length 1.181 in [30 mm] 0.5 in [12.70 mm] Width/Dia. Weight 0.023 lbs [10.43 g]

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: BNC Female Bulkhead Mount Connector Solder Attachment Solder Cup Terminal, .350 inch D Hole PE4015

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • Fax: (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com



BNC Female Bulkhead Mount Connector Solder Attachment Solder Cup Terminal, .350 inch D Hole



RF Connectors Technical Data Sheet

PE4015

Material Specifications

Description	Material	Plating	
Contact	Brass	Gold 30 µin minimum	
Insulation	PTFE		
Body	Brass	Nickel 100 μin minimum	

Environmental Specifications

Temperature

Operating Range

-65 to +165 deg C

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:

BNC Female Bulkhead Mount Connector Solder Attachment Solder Cup Terminal, .350 inch D Hole from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99.4% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: BNC Female Bulkhead Mount Connector Solder Attachment Solder Cup Terminal, .350 inch D Hole PE4015

URL: https://www.pasternack.com/bnc-female-standard-solder-cup-terminal-connector-pe4015-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Pasternack does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Pasternack does not assume any liability arising out of the use of any part or documentation.

PE4015 CAD Drawing

BNC Female Bulkhead Mount Connector Solder Attachment Solder Cup Terminal, .350 inch D Hole

